

To upgrade to new Ceton Echo firmware:

- Makes sure the [Echo Settings plugin](#) is installed on the Media Center PC
- Power on Echo
- On Echo: go to **Extras / Extras Library / Ceton Echo Settings**
- Go to: **About** and make sure **Update Channel** is set to **beta**
- Click **Save** then **Ok**
- Go to: **About** again and arrow over to the data field next **Echo Version**. It should say something like **2012.1202.1302**. With the data field highlighted click **Ok**. It can take a little while for the beta updates to start showing.
- On the **Echo Updates** screen, click on the latest update. It should say something like **Echo Update 2012.1213.1022 (beta)**.
- On the next screen click on **Update**, then click **Yes**
- This will download and install the new firmware. You will see a black Ceton screen that has a status bar and says **Updating. do not unplug echo. Do not power off the Echo or remove it from the network during the update process.**
- Once the update is installed, Echo reboots and reconnects to the Media Center PC.
- You're all set to go!

A screen shot walk through of the process is below:





echo | about

Ceton Echo | Windows Media Center Extender

Save
Cancel

Copyright © 2012 Ceton Corporation. All rights reserved.

Echo Version: 2012.1202.1302

Settings Version: 12.12.04.0935

Update Channel

- stable
- beta

Download and install updates for your Ceton Echo

echo | update

ECHO UPDATES

Save
Cancel

MAC Address: 00:22:2c:90:1b:61

Update Channel: beta

Current Version: 2012.1202.1302

Update(s) available:

Echo Update 2012.1213.1022 [beta]



ceton



updating. do not unplug echo